

Transistor Type No.	N/P G/S	Manufacturer	Lead Ident.	Out-line	Maximum (V)			Maximum		Max. T.(°C)	Frequency Resp.(MHz)	Leakage		Gain	
					V <sub>CB</sub>	V <sub>CE</sub> '	V <sub>ES</sub>	I <sub>C</sub>	Power			I <sub>CBQ</sub> @ V <sub>CB</sub>	V <sub>CB</sub>	h <sub>FE</sub> @ I <sub>C</sub>	
2N3119	N S	RCA	211	TO 5	100	80	4.0	.500A	1.000W	200J	250.000G	50NA	60V	120	
2N3123	N S	TRW	211	TO 5	60	30	5.0		3.000W		400.000G	10NA	50V	170	.150A
2N3127	P G	MOT	217	TO 72	25	20	.7	.050A	.100W	100J	400.000G	3UA	10V	46	.003A
2N3133	P S	MOT GIC	210	TO 5	50	35	4.0	.600A	.600W	200J	200.000G	50NA	30V	70	.150A
2N3134	P S	MOT GIC	210	TO 5	50	35	4.0	.600A	.600W	200J	200.000G	50NA	30V	170	.150A
2N3135	P S	MOT GIC	210	TO 18	50	35	4.0	.600A	.400W	200J	200.000G	50NA	30V	70	.150A
2N3136	P S	MOT GIC ETC	210	TO 18	50	35	4.0	.600A	.400W	200J	200.000G	50NA	30V	170	.150A
2N3137	N S	FSC ITT SES	211	TO 5	40	20	4.0		.600W	200J	500.000G	50NA	20V	70	
2N3146	P G	III	605	TO 3	150	65	60.0	15.000A	150.000W	100J	.200G	10MA	150V	60	
2N3147	P G	III	605	TO 3	180	75	80.0	15.000A	150.000W	100J	.200G	10MA	180V	600	
2N3149	N S	STC SOL	561	TO114	80	80	10.0	70.000A	300.000W	200J	.100G	2MA	80V	20	50.000A
2N3150	N S	STC SOL	561	TO114	100	100	10.0	70.000A	300.000W	200J	.100G	2MA	100V	20	50.000A
2N3151	N S	STC SOL	561	TO114	150	150	10.0	70.000A	300.000W	200J	.100G	2MA	150V	20	50.000A
2N3163	P S	STC	561	TO 61	40	40	10.0	3.000A	85.000W	200J	HF AMP	1MA	40V	20	1.000A
2N3164	P S	STC	561	TO 61	60	60	10.0	3.000A	85.000W	200J	HF AMP	1MA	60V	20	1.000A
2N3165	P S	STC	561	TO 61	80	80	10.0	3.000A	85.000W	200J	HF AMP	1MA	80V	20	1.000A
2N3166	P S	STC	561	TO 61	100	100	10.0	3.000A	85.000W	200J	HF AMP	1MA	100V	20	1.000A
2N3167	P S	STC	731	TO 53	40	40	10.0	3.000A	85.000W	200J	HF AMP	1MA	40V	20	1.000A
2N3168	P S	STC	731	TO 53	60	60	10.0	3.000A	85.000W	200J	HF AMP	1MA	60V	20	1.000A
2N3169	P S	STC	731	TO 53	80	80	10.0	3.000A	85.000W	200J	HF AMP	1MA	80V	20	1.000A
2N3170	P S	STC	731	TO 53	100	100	10.0	3.000A	85.000W	200J	HF AMP	1MA	100V	20	1.000A
2N3171	P S	STC	605	TO 3	40	40	10.0	3.000A	75.000W	200J	HF AMP	1MA	40V	20	1.000A
2N3172	P S	STC	605	TO 3	60	60	10.0	3.000A	75.000W	200J	HF AMP	1MA	60V	20	1.000A
2N3173	P S	STC	605	TO 3	80	80	10.0	3.000A	75.000W	200J	HF AMP	1MA	80V	20	1.000A
2N3174	P S	STC	605	TO 3	100	100	10.0	3.000A	75.000W	200J	HF AMP	1MA	100V	20	1.000A
2N3175	P S	STC	561	TO 61	40	40	10.0	5.000A	85.000W	200J	HF AMP	1MA	40V	16	2.000A
2N3176	P S	STC	561	TO 61	60	60	10.0	5.000A	85.000W	200J	HF AMP	1MA	60V	16	2.000A
2N3177	P S	STC	561	TO 61	80	80	10.0	5.000A	85.000W	200J	HF AMP	1MA	80V	16	2.000A
2N3178	P S	STC	561	TO 61	100	100	10.0	5.000A	85.000W	200J	HF AMP	1MA	100V	16	2.000A
2N3179	P S	STC	731	TO 53	40	40	10.0	5.000A	85.000W	200J	HF AMP	1MA	40V	16	2.000A
2N3180	P S	STC	731	TO 53	60	60	10.0	5.000A	85.000W	200J	HF AMP	1MA	60V	16	2.000A
2N3181	P S	STC	731	TO 53	80	80	10.0	5.000A	85.000W	200J	HF AMP	1MA	80V	16	2.000A
2N3182	P S	STC	731	TO 53	100	100	10.0	5.000A	85.000W	200J	HF AMP	1MA	100V	16	2.000A
2N3183	P S	STC	605	TO 3	40	40	10.0	5.000A	75.000W	200J	HF AMP	1MA	40V	16	2.000A
2N3184	P S	STC	605	TO 3	60	60	10.0	5.000A	75.000W	200J	HF AMP	1MA	60V	16	2.000A
2N3185	P S	STC	605	TO 3	80	80	10.0	5.000A	75.000W	200J	HF AMP	1MA	80V	16	2.000A
2N3186	P S	STC	605	TO 3	100	100	10.0	5.000A	75.000W	200J	HF AMP	1MA	100V	16	2.000A
2N3187	P S	STC	561	TO 61	40	40	10.0	5.000A	85.000W	200J	HF AMP	1MA	40V	16	3.000A
2N3188	P S	STC	561	TO 61	60	60	10.0	5.000A	85.000W	200J	HF AMP	1MA	60V	16	3.000A
2N3189	P S	STC	561	TO 61	80	80	10.0	5.000A	85.000W	200J	HF AMP	1MA	80V	16	3.000A
2N3190	P S	STC	561	TO 61	100	100	10.0	5.000A	85.000W	200J	HF AMP	1MA	100V	16	3.000A
2N3191	P S	STC	731	TO 53	40	40	10.0	5.000A	85.000W	200J	HF AMP	1MA	40V	16	3.000A
2N3192	P S	STC	731	TO 53	60	60	10.0	5.000A	85.000W	200J	HF AMP	1MA	60V	16	3.000A