

2 N 3223		Si-N	=2N3220: 80V, hFE=40...120	49a	=TO-111			2N5002, 2N5004, 2N5284...85
2 N 3224	USA	SI-P	LF Drv 100V, 0.7W, >60MHz, hfe>20	2a	TO-5			BSW 40, 2N3634...37, 2SA606, 2SA712
2 N 3225	USA	SI-P	=2N3224: >80MHz, hfe>40	2a	TO-5			BSW 40, 2N3634...37, 2SA606, 2SA712
2 N 3226	Sca,Sol,Ssi	SI-N	LF P, 35V, 5A, 75W	23a	TO-3			BD 245, BDV 91, BDX 91, 2N4914...15, ++
2 N 3227	USA,Mot,Tix	SI-N	SS, 40V, 0.5A, 0.36W, <23/28ns	2a	TO-18			BSS 10, BSX 26, BSX 39, 2N3261
2 N 3228	Rca,Sgs,Tag	50Hz-Thy	200V, 3.2A(Tc=75°), 5A=, Igt/Ih<15/<20mA	22a	TO-66	(TAG 626-600) <sup>5</sup>	17e	2N3525, 2N4101, BSIC0513L, TAG 671-200
2 N 3229	Fer,Rca,Ssi	SI-N	VHF P, 105V, 2.5A, PQ=15W(150MHz)	49a	TO-60			-
2 N 3230	Fer,Rca,Tsc	SI-N-Darl	S P, 80V, 7A, 25W, hFE=1000					-
2 N 3231	Fer,Rca,Tsc	SI-N-Darl	=2N3230: 100V					-
2 N 3232	USA,Mot	SI-N	LF,S P, 60/60V, 7.5A, 117W, >1MHz	23a	TO-3	2N3055	23a	BD 245A, BD 311, BDV 91, BDX 91, ++
2 N 3233	USA,Mot	SI-N	=2N3232: 100/100V	23a	TO-3	2N3055	23a	BD 245C, BDV 95, BDX 95, 2N5632...34, ++
2 N 3234	USA,Mot	SI-N	=2N3232: 160/160V	23a	TO-3	(2SC3281) <sup>4</sup>	=16j	BD 245D, BDX 11, 2N3442, 2SC2260...62, ++
2 N 3235	USA	SI-N	LF,S P, 55/55V, 15A, 117W, >1MHz	23a	TO-3			BD 315, BD 545A, BD 745A, 2N3055, ++
2 N 3236	USA	SI-N	LF,S P, 90/90V, 15A, 150W, >1MHz	23a	TO-3			BD 317, BD 745C, 2N3772, 2N5629...31, ++
2 N 3237	USA	SI-N	LF,S P, 90/75V, 20A, 200W, >1MHz	23a	TO-3			BDY 29, MJ 802, 2N3772, 2SD797
2 N 3238	USA,Mot	SI-N	LF,S P, 80/80V, 15A, 150W, >1MHz, sat<3V(10A)	23a	TO-3			BD 315, BD 545B, BD 745B, 2N3772, ++
2 N 3239	USA,Mot	SI-N	=2N3238: sat<1V(10A)	23a	TO-3			BD 315, BD 545B, BD 745B, 2N3772, ++
2 N 3240	USA,Mot	SI-N	=2N3238: 160/160V, sat<1V(10A)	23a	TO-3			BD 745F, BDW 12, 2N3773, 2SD752, ++
2 N 3241	USA	SI-N	Uni, 30/25V, 0.1A, 0.5W, >50MHz, hfe=70...250	2a	=TO-1			BC 168, BC 183, BC 238, BC 548, ++
2 N 3241 A		SI-N	=2N3241: 0.2A, hfe=100...200	2a	=TO-1			BC 168, BC 183, BC 238, BC 548, ++
2 N 3242	USA	SI-N	Uni, 30/25V, 0.2A, 0.5W, >50MHz, hfe=100...375	2a	=TO-1			BC 168, BC 183, BC 238, BC 548, ++
2 N 3242 A		SI-N	=2N3242: 40/40V, 0.3A, hfe=125...300	2a	=TO-1			BC 167, BC 182, BC 237, BC 547, ++
2 N 3244(S)	USA,Mot,Tix	SI-P	S, 40V, 1A, 1W, <50/185ns	2a	TO-5			2N3467...68, 2SA717, 2SA799
2 N 3245(S)	USA,Mot,Tix	SI-P	S, 50V, 1A, 1W, <55/165ns	2a	TO-5			2N3468, 2SA717, 2SA799
2 N 3246	USA,Nsc	SI-N	Uni, 60V, 0.05A, 0.35W, >60MHz	2a	TO-18			BC 174, BC 182, BC 190, BC 546, ++
2 N 3247	Upi	SI-N	=2N3246: Min, 0.15W	=7c				-
2 N 3248	USA,Mot,Nsc	SI-P	S, 15V, 0.2A, 0.36W, >250MHz, <20/80ns	2a	TO-18			BSX 36
2 N 3249	USA,Mot,Nsc	SI-P	=2N3248: >300MHz	2a	TO-18			BSX 36
2 N 3250	Fch,Mot,Nsc	SI-P	S, 50/40V, 0.2A, 0.36W, >250MHz, hFE=50, <70/225ns	2a	TO-18			BSW 24, 2N2906...07(A)
			(2N3946)					
2 N 3250 A		SI-P	=2N3250: 60/60V	2a	TO-18			BSW 24, 2N2906...07(A)
2 N 3251	Fch,Mot,Nsc	SI-P	=2N3250: hFE=100...300, >300MHz, <70/250ns	2a	TO-18			BSW 24, 2N2906...07(A)
			(2N3947)					
2 N 3251 A		SI-P	=2N3251: 60/60V	2a	TO-18			BSW 24, 2N2906...07(A)
2 N 3252(S)	Fch,Mot,Nsc	SI-N	S, 60/30V, 1A, 1W, hFE=30...90, >200MHz, <45/70ns	2a	TO-5			BSS 27, BSV 77, BSV 95, 2N5189, ++
			(2N3252S)					
2 N 3253(S)		SI-N	S, 75/40V, 1A, 1W, hFE=25...75, >175MHz, <50/70ns	2a	TO-5			BSV 95, 2N3735, 2SC1069
2 N 3254	Mot,Ssi,Uni	F-Thy	15V, 0.25A(Ta=55°C), Igt/Ih<0.02/<2mA	2a	TO-46			(2N2322A) <sup>6</sup>
2 N 3255		F-Thy	=2N3254: 30V	2a	TO-46			(2N2323A) <sup>6</sup>
2 N 3256		F-Thy	=2N3254: 60V	2a	TO-46			(2N2324A) <sup>6</sup>
2 N 3257		F-Thy	=2N3254: Igt/Ih<0.2/<3mA	2a	TO-46	(TAG 103 X) <sup>6</sup>	2a	BRY58/30, TAG06Y, 2N6605,(2N2322, TIC44) <sup>6</sup>
2 N 3258		F-Thy	=2N3255: Igt/Ih<0.2/<3mA	2a	TO-46	(TAG 103 X) <sup>6</sup>	2a	BRY58/30, TAG06Y, 2N6605,(2N2323, TIC44) <sup>6</sup>
2 N 3259		F-Thy	=2N3256: Igt/Ih<0.2/<3mA	2a	TO-46	(BRX 49) <sup>6</sup>	7a	BRY 58/60, TAG 06YY, 2N6606S,(TIC 46) <sup>6</sup>
2 N 3260	Idi,Stc	SI-N	S P, 200/200V, 30A, 200W	49m	TO-61			2N6324...25
2 N 3261	USA,Fer	SI-N	SS, 40V, 0.5A, 0.3W, <13/16ns	2a	TO-18			BSS 10, BSX 26, BSX 39
2 N 3262	USA,Fer,Tix	SI-N	S, 100V, 1.5A, 1W, <40/750ns	2a	TO-39			2SD854
2 N 3263	USA,Rca	SI-N	S P, 150V, 25A, 84W, >20MHz					-
2 N 3264	USA,Rca	SI-N	=2N3263: 120V					-
2 N 3265	USA,Rca,Tix	SI-N	=2N3263: 125W	49m	TO-63			2N2817...18, 2N2821...22
2 N 3266	USA,Rca,Tix	SI-N	=2N3263: 120V, 125W	49m	TO-63			2N2817...18, 2N2821...22, 2N5539
2 N 3267	Ssi	Ge-P	UHF, 15V, 0.02A, 0.075W, >900MHz	5g	TO-72			AF 139, AF 239(S), 2N3283...86
2 N 3268	USA	SI-N	Uni, 45V, 0.025A, 0.15W, >2.5MHz	2a	TO-5			BC 167, BC 182, BC 237, BC 547, ++
2 N 3273	Ssi,Uni	50Hz-Thy	100V, 2.2A(Tc=85°), Igt/Ih<0.2/<2mA	2a	TO-5	(TIC 106 M) <sup>4</sup>	17e	(TAG 106A, C 106A1, X 0403A, TAG 108A) <sup>4</sup>
2 N 3274		50Hz-Thy	=2N3273: 200V	2a	TO-5	(TIC 106 M) <sup>4</sup>	17e	(TAG 106B, C 106B1, X 0403B, TAG 108B) <sup>4</sup>
2 N 3275		50Hz-Thy	=2N3273: 300V	2a	TO-5	(TIC 106 M) <sup>4</sup>	17e	(TAG 106C, C 106C1, X 0403C, TAG 108C) <sup>4</sup>
2 N 3276		50Hz-Thy	=2N3273: 400V	2a	TO-5	(TIC 106 M) <sup>4</sup>	17e	(TAG 106D, C 106D1, X 0403D, TAG 108D) <sup>4</sup>
2 N 3277	Fch,Isi,Sol	P-FET	Uni, 25V, Idss>0.15mA, Up<5V	5n	TO-33			2N5473...74, 2N5797
2 N 3278	Fch,Isi,Sol	P-FET	Uni, 25V, Idss>0.4mA, Up<8V	5n	TO-33			BF 320A, 2N3809, 2N3820, 2N5475
2 N 3279	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 30V, 0.05A, 500MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3280	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 30V, 0.05A, 500MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3281	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 30V, 0.05A, 400MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3282	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 30V, 0.05A, 400MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3283	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 25V, 0.05A, 400MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3284	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 25V, 0.05A, 400MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3285	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 20V, 0.05A, 400MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3286	Mot,Ssi,Sty	Ge-P	VHF Inp,Mx,Os, In, 20V, 0.05A, 400MHz	5g	TO-72			AF 139, AF 239(S)
2 N 3287	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 40V, 0.05A, 600MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3288	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 40V, 0.05A, 600MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3289	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 30V, 0.05A, 500MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3290	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 30V, 0.05A, 500MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3291	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 25V, 0.05A, 600MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3292	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 25V, 0.05A, 600MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3293	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 20V, 0.05A, 600MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3294	Mot,Sca,Ssi	SI-N	VHF Inp,Mx,Os, 20V, 0.05A, 600MHz	5g	TO-72			BF 310, BF 314, BF 502, BF 505, BF 507++
2 N 3295(S)	Mot,Sca,Ssi	SI-N	HF Drv, 60V, 0.25A, PEP=0.3W(30MHz)	2a	TO-5			MRF 402, MRF 8003
2 N 3296	Mot,Sca,Ssi	SI-N	HF Drv,Out, 60V, 0.7A, PEP=3W(30MHz)	49m	TO-102			-
2 N 3297	Mot,Sca,Ssi	SI-N	HF P, 60V, 1.5A, PEP=12W(30MHz)	23a	TO-3			-
2 N 3298	Mot,Sca,Ssi	SI-N	HF Os,Drv, 25V, 0.1A, PQ=0.06W(80MHz)	2a	TO-18			BFX 59
2 N 3299(S)	USA,EUR	SI-N	S, 60V, 0.5A, 0.8W, <60/150ns, hFE=40...120	2a	TO-5			BSS 27, BSV 77, BSV 95, 2N5189, ++
2 N 3300(S)	USA,EUR	SI-N	=2N3299: hFE=100...300	2a	TO-5			BSS 27, BSV 77, BSV 95, 2N5189, ++
2 N 3301	USA,EUR	SI-N	=2N3299: 0.36W	2a	TO-18			BSS 26, BSV 59, BSX 49, 2N4014, ++
2 N 3302	USA,EUR	SI-N	=2N3299: 0.36W, hFE=100...300	2a	TO-18			BSS 26, BSV 59, BSX 49, 2N4014, ++
2 N 3303	USA,EUR	SI-N	S,Drv, 25V, 1A, 0.6W, >450MHz, <15/25ns	2a	=TO-5			BSS 28...29, BSV 69, 2N3724A, 2N5189, ++
2 N 3304	USA,Mot,Tix	SI-P	S, 6V, 0.1A, 0.3W, >500MHz, <60/60ns	2a	TO-18			BSX 36
2 N 3305	USA	SI-P	Uni, 50V, 0.6W, >20MHz, hFE=40...120	2a	TO-5			BC 161, BC 303...304, BSW 23, 2N2303, ++
2 N 3306	USA	SI-P	=2N3305: hFE=100...300	2a	TO-5			BC 161, BC 303...304, BSW 23, 2N2303, ++
2 N 3307	USA,Mot	SI-P	VHF Inp,Mx,Os, 40V, 0.05A, 0.2W, >300MHz	5g	TO-72			BF 324, BF 414, BF 506, BF 914, BF 936++
2 N 3308	USA,Mot	SI-P	VHF Inp,Mx,Os, 30V, 0.05A, 0.2W, >300MHz	5g	TO-72			BF 324, BF 414, BF 506, BF 914, BF 936++
2 N 3309	Mot,Tho,Tix	SI-N	VHF Drv,Out, 50V, 0.5A, PQ=2W(250MHz)	2a	TO-39			BFS 23, BLY 34, 2SC2419
2 N 3309 A	Mot	SI-N	=2N3309: 60V, PQ=2.2W(250MHz)	2a	TO-39			BFS 23, BLY 34, 2SC2419
2 N 3310	Mot,Sty	SI-N	VHF Drv,Out, 35V, 0.2A, 0.3W, >300MHz	=2a	TO-38			BFR 36, BFR 98, BFX 55, MRF 607, ++
2 N 3311	USA,Mot	Ge-P	S P, 30V, 5A, 170W, hFE=60...120	38a	TO-36			2N1980...82, 2N2075...82, 2N2491...93
2 N 3312	USA,Mot	Ge-P	=2N3311: 45V	38a	TO-36			2N1980...82, 2N2075...82, 2N2491...93