

2N2605	TO-46	60	45	6	10	45	100 150	300 600	0.01 0.5 10	5 5 5	0.5	0.7	0.9	10	6	30	0.5		3	1	62
JAN2N2605	TO-46	70	60	6	10	50	100 150	300 600	0.010 0.5	5 5	0.5	0.7	0.9	10	6	30	300	0.5	3	1	62
2N3547	TO-18	60	60	6	25	45	60 100 75	500 10	0.01 1 10	5 5 5	1		1	10	8	45	150	1	5	1	62
2N3548	TO-18	60	45	6	10	45	100 150	300 600	0.01 0.1 10	5 5 5	1		1	10	8	60	150	1	4	1	62
2N3549	TO-18	60	60	6	10	45	100 150 200	500 0.100 1	0.010 0.100 1	5 5 5	1		1	10	8	60	150	1	4	1	62
2N3550	TO-18	60	45	8	1.0	45	125 200 300	600 0.010 1	0.001 0.010 1	5 5 5	0.5	0.7	0.9	5	8	60	150	1	4	1	62
2N3799	TO-18	60	60	5	10	50	75 225 300 300 300	300 0.01 0.1 0.5 1	0.001 0.01 0.1 0.5 1	5 5 5 5 5	0.2 0.25		0.7 0.8	0.01 1	4	30	0.5	1.5 1.5 4 2.5	9 10 11 12		62
2N3962	TO-18	60	60	6	10	50	100 100	300 450	0.010 1.0	5 5	0.25		0.9	10	6	40	160	0.5	3 3 3 10	2 3 4 5	62
2N3963	TO-18	80	80	6	10	70	100 100	300 450	0.010 1.0	5 5	0.25		0.9	10	6	40	160	0.5	3 3 3 10	2 3 4 5	62
2N3964	TO-18	45	45	6	10	40	250 250	500 600	0.010 1	5 5	0.25		0.9	10	6	40	160	0.5	2 2 2 4	2 3 4 5	62
2N3965	TO-18	60	60	6	10	50	250 250	500 600	0.010 1	5 5	0.25		0.9	10	6	40	160	0.5	2 2 2 4	2 3 4 5	62
2N4248	TO-106	40	40	5	10	40	50		0.1	5	0.25		10	6					3	2	62
2N4249	TO-106	60	60	5	10	40	100	300	0.1	5	0.25		10	6					3 3 3	2 4 6	62

Test Conditions:

- $I_C = 10 \mu A$, $V_{CE} = 5V$,
 $R_G = 10 k\Omega$, $BW = 15.7 kHz$
- $I_C = 20 \mu A$, $V_{CE} = 5V$,
 $R_G = 10 k\Omega$, $BW = 15.7 kHz$
- $I_C = 20 \mu A$, $V_{CE} = 5V$,
 $R_G = 10 k\Omega$, $BW = 1.5 kHz$
 $f = 10 kHz$
- $I_C = 20 \mu A$, $V_{CE} = 5V$,
 $f = 1 kHz$, $BW = 150 Hz$,
 $R_G = 10 k\Omega$
- $I_C = 20 \mu A$, $V_{CE} = 5V$,
 $f = 100 Hz$, $BW = 15 Hz$,
 $R_G = 10 k\Omega$
- $I_C = 250 \mu A$, $V_{CE} = 5V$,
 $R_G = 1 k\Omega$, $f = 1 kHz$,
 $BW = 150 Hz$
- $I_C = 10 \mu A$, $V_{CE} = 5V$,
 $R_G = 10 k\Omega$, $f = 1 kHz$
 $BW = 200$
- $I_C = 100 \mu A$, $V_{CE} = 5V$,
 $R_S = 3K$, $f = 1 kHz$
- $V_{CE} = 10V$, $I_C = 100 \mu A$, $R_G = 3 k\Omega$
 $f = 10 kHz$, $BW = 2 kHz$
- $V_{CE} = 10V$, $I_C = 100 \mu A$, $R_G = 3 k\Omega$
 $f = 100 Hz$, $BW = 20 Hz$
- $V_{CE} = 10V$, $I_C = 100 \mu A$, $R_G = 3 k\Omega$
 $f = 1 kHz$, $BW = 200 Hz$
- $V_{CE} = 10V$, $I_C = 100 \mu A$, $R_G = 3 k\Omega$
 $BW = 15.7 Hz$