

BD 477 B	Si-N-Darl	=BD 477A: 45V	14h	(BD 679)	14h	8
BD 487	Si-P	S-L, 30V, 12A, 12,5W, >50MHz	13h	-		
BD 488	Si-P	=BD 487: 45V	13h	-		
BD 500	Si-P	NF-L, 60V, 10A, 75W, >5MHz	17j	BD 810	17j	
BD 500 A	Si-P	=BD 500: 70V	17j	BD 810	17j	
BD 500 B	Si-P	=BD 500: 90V	17j	BD 810	17j	
BD 501	Si-N	NF-L, 60V, 10A, 75W, >5MHz	17j	BD 809	17j	
BD 501 A	Si-N	=BD 501: 70V	17j	BD 809	17j	
BD 501 B	Si-N	=BD 501: 90V	17j	BD 809	17j	
BD 505	Si-N	NF-Tr/E, 30V, 2A, 10W, 250MHz	13m	(2SC4135)	30j	4
BD 506	Si-P	NF-Tr/E, 30V, 2A, 10W, 250MHz	13m	(2SA1593)	30j	4
BD 507	Si-N	=BD 505: 40V	13m	(2SC4135)	30j	4
BD 508	Si-P	=BD 506: 40V	13m	(2SA1593)	30j	4
BD 509	Si-N	=BD 505: 50V	13m	(2SC4135)	30j	4
BD 510	Si-P	=BD 506: 60V	13m	(2SA1593)	30j	4
BD 512	MOS-P-FET-e	V-MOS, NF-L, 60V, 1,5A, 10W	13j	-		
BD 515	Si-N	NF-Tr/E, 45V, 2A, 10W, 160MHz	13m	(2SC4135)	30j	4
BD 516	Si-P	NF-Tr/E, 45V, 2A, 10W, 125MHz	13m	(2SA1593)	30j	4
BD 517	Si-N	=BD 515: 60V	13m	(2SC4135)	30j	4
BD 518	Si-P	=BD 516: 60V	13m	(2SA1593)	30j	4
BD 519	Si-N	=BD 515: 80V	13m	(2SC4135)	30j	4
BD 520	Si-P	=BD 516: 80V	13m	(2SA1593)	30j	4
BD 522	MOS-N-FET-e	V-MOS, NF-L, 60V, 1,5A, 10W	13j	-		
BD 524	Si-N	TV-HA-Tr, 160V, 0,8A, 5W, 100MHz	14h	2SC3117	14h	
BD 525	Si-N	NF-Tr/E, 60V, 2A, 10W, 150MHz	13m	(2SC4135)	30j	4
BD 526	Si-P	NF-Tr/E, 60V, 2A, 10W, 100MHz	13m	(2SA1593)	30j	4
BD 527	Si-N	=BD 525: 80V	13m	(2SC4135)	30j	4
BD 528	Si-P	=BD 526: 80V	13m	(2SA1593)	30j	4
BD 529	Si-N	=BD 525: 100V	13m	(2SC4135)	30j	4
BD 530	Si-P	=BD 526: 100V	13m	(2SA1593)	30j	4
BD 533(A)	Si-N	NF-L, 45V, 4A, 50W, >3MHz	17j	BD 243 C	17j	
BD 533 FI	Si-N	=BD 533: Iso, 22W	17c	2SD1411	17c	
BD 534(A)	Si-P	NF-L, 45V, 4A, 50W, >3MHz	17j	BD 244 C	17j	
BD 534 FI	Si-P	=BD 534: Iso, 22W	17c	2SB1018	17c	
BD 535(A)	Si-N	=BD 533: 60V	17j	BD 243 C	17j	
BD 536(A)	Si-P	=BD 534: 60V	17j	BD 244 C	17j	
BD 537(A)	Si-N	=BD 533: 80V	17j	BD 243 C	17j	
BD 538(A)	Si-P	=BD 534: 80V	17j	BD 244 C	17j	
BD 539	Si-N	NF-L, 40V, 5A, 45W, >3MHz	17j	BD 809	17j	
BD 539 A	Si-N	=BD 539: 60V	17j	BD 809	17j	
BD 539 B	Si-N	=BD 539: 80V	17j	BD 809	17j	
BD 539 C	Si-N	=BD 539: 100V	17j	BD 243 C	17j	
BD 539 D	Si-N	=BD 539: 120V	17j	2SC2334	17j	
BD 540	Si-P	NF-L, 40V, 5A, 45W, >3MHz	17j	BD 810	17j	
BD 540 A	Si-P	=BD 540: 60V	17j	BD 810	17j	
BD 540 B	Si-P	=BD 540: 80V	17j	BD 810	17j	
BD 540 C	Si-P	=BD 540: 100V	17j	-		
BD 540 D	Si-P	=BD 540: 120V	17j	-		
BD 543	Si-N	NF-L, 40V, 8A, 70W, >3MHz	17j	BD 809	17j	
BD 543 A	Si-N	=BD 543: 60V	17j	BD 809	17j	
BD 543 B	Si-N	=BD 543: 80V	17j	BD 809	17j	
BD 543 C	Si-N	=BD 543: 100V	17j	2SC2334	17j	
BD 543 D	Si-N	=BD 543: 120V	17j	2SC2334	17j	
BD 544	Si-P	NF-L, 40V, 8A, 70W, >3MHz	17j	BD 810	17j	
BD 544 A	Si-P	=BD 544: 60V	17j	BD 810	17j	
BD 544 B	Si-P	=BD 544: 80V	17j	BD 810	17j	