

2 N 2570	Amp,Phi	Si-N	Chopper, 20V, 0,1A, 0,3W, >100MHz	2a	TO-18					2N2432, 2N4138
2 N 2571	Amp	Si-N	Chopper, 20V, 0,5A, 0,3W, >100MHz	2a	TO-18					-
2 N 2572	Amp	Si-N	Chopper, 20V, 0,5A, 0,3W, >100MHz	2a	TO-18					-
2 N 2573	Mot,Slid	50Hz-Thy	25V, 17A(Tc=85°), 25A=, Igt/Ih<40/10mA	23a	TO-3					2N3668
2 N 2574		50Hz-Thy	=2N2573: 50V	23a	TO-3					2N3668
2 N 2575		50Hz-Thy	=2N2573: 100V	23a	TO-3					2N3668
2 N 2576		50Hz-Thy	=2N2573: 200V	23a	TO-3					2N3669
2 N 2577		50Hz-Thy	=2N2573: 300V	23a	TO-3					2N3670
2 N 2578		50Hz-Thy	=2N2573: 400V	23a	TO-3					2N3670
2 N 2579		50Hz-Thy	=2N2573: 500V	23a	TO-3					-
2 N 2580(M)	Del,Stc	Si-N	S P, 400/400V, 10A, 150W, hFE=10...40	38a	TO-36					-
2 N 2581	Del,Stc	Si-N	=2N2580: hFE=25...65	38a	TO-36					-
2 N 2582	Del,Stc	Si-N	S P, 500/500V, 10A, 150W, hFE=10...40	38a	TO-36					-
2 N 2583	Del,Stc	Si-N	=2N2582: hFE=25...65	38a	TO-36					-
2 N 2584	Stc	Si-N	S P, 600/600V, 10A, 150W, hFE=10...40	38a	TO-36					-
2 N 2585	Stc	Si-N	=2N2584: hFE=25...65	38a	TO-36					-
2 N 2586	USA,EUR,Mic	Si-N	LF Inp In, 60V, 0,03A, 0,3W, 63MHz	2a	TO-18					2N2483...84, 2N3117, 2SC2240, 2SC2390, ++
2 N 2587	Mot	Ge-P	UHF, 30V, 0,1A, 0,15W, >320MHz	2a	TO-18					2N3283...86
2 N 2588	Tix	Ge-P	HF, 40V, 0,03A, 0,15W, >75MHz	2a	TO-18					AF 106, AF 109R, AF 306
2 N 2589	Stc	Si-N	S P, 150/150V, 7A, 85W	49m	TO-63					2N5542
2 N 2590	USA	Si-P	Uni, 100V, 0,05A, 0,4W, >50MHz, hFE>40	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2591	USA	Si-P	=2N2590: >70MHz, hFE>70	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2592	USA	Si-P	=2N2590: >90MHz, hFE>115	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2593	USA	Si-P	=2N2590: >110MHz, hFE>160	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2594	USA,Tix	Si-N	LFS, 80V, 1A, 1W, >40MHz	2a	TO-5					BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 N 2595	USA	Si-P	Uni, 80V, 0,05A, 0,4W, >30MHz, hFE>15	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2596	USA	Si-P	=2N2595: >40MHz, hFE>30	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2597	USA	Si-P	=2N2595: >60MHz, hFE>60	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...16, ++
2 N 2598	USA	Si-P	Uni, 125V, 0,05A, 0,4W, >30MHz, hFE>20	2a	TO-46					BF 398, 2SA970, 2SA1049, 2SB716(A), ++
2 N 2599(A)	USA	Si-P	=2N2598: >40MHz, hFE>40	2a	TO-46					BF 398, 2SA970, 2SA1049, 2SB716(A), ++
2 N 2600(A)	USA	Si-P	=2N2598: >60MHz, hFE>60	2a	TO-46					BF 398, 2SA970, 2SA1049, 2SB716(A), ++
2 N 2601	USA	Si-P	Uni, 60V, 0,05A, 0,4W, >20MHz, hFE>18	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...716, ++
2 N 2602	USA	Si-P	=2N2601: >40MHz, hFE>36	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...716, ++
2 N 2603	USA	Si-P	=2N2601: >60MHz, hFE>76	2a	TO-46					BSS 68, BSV 68, 2SA970, 2SB715...716, ++
2 N 2604	USA,EUR,Mic	Si-P	LFS, In, 60V, 0,03A, 0,4W, >30MHz, hFE=40...120	2a	TO-46	2SA1124	7c(9mm)			2SA970, 2SA1016, 2SA1038...39, 2SA1136, ++
2 N 2605(A)	USA,EUR,Mic	Si-P	=2N2604: hFE=100...300(A: 150...300)	2a	TO-46	2SA1124	7c(9mm)			2SA970, 2SA1016, 2SA1038...39, 2SA1136, ++
2 N 2606	USA,Mot,Tix	P-FET	Uni, 30V, Idss>0,1mA, Up<4V	2a	TO-18					2N5797
2 N 2607	USA,Mot,Tix	P-FET	Uni, 30V, Idss>0,3mA, Up<4V	2a	TO-18					2N5020
2 N 2608	USA,Mot,Tix	P-FET	Uni, 30V, Idss>0,9mA, Up<4V	2a	TO-18					2N5460
2 N 2609	USA,Mot,Tix	P-FET	Uni, 30V, Idss>2mA, Up<4V	2a	TO-18					2N5461
2 N 2610	USA	Si-N	LFS, 45V, 0,025A, 0,15W	≈1a	TO-22					BC 167, BC 182, BC 237, BC 547, ++
2 N 2611	Sca,Ssi	Si-N	LFS, 120V, 1A, >4MHz	43m	≈TO-37					(BD 424, BD 524, 2SC2384, 2SC2481, ++)
2 N 2612	USA	Ge-P	LFS P, 65V, 15A, 75W	23a	TO-3					2N1551...52, 2N1555...56, 2N1559...60
2 N 2613	Rca,Spe	Ge-P	LF, 30V, 0,05A, 0,12W	2a	TO-1	AC 151	2a			AC 125...126, AC 151, 2SB54, 2SB56
2 N 2614	Rca,Spe	Ge-P	LF, 40V, 0,05A, 0,12W	2a	TO-1	AC 151	2a			2N1191...94, 2SB56A
2 N 2615	USA,Sgs	Si-N	VHF,IF, 30V, 0,3W, >500MHz	2a	TO-18					BF 224...225, BFR 37, BFW 30, BFX 73, ++
2 N 2616	USA,Sgs	Si-N	VHF,IF, 30V, 0,05A, 0,3W, >600MHz	2a	TO-18					BF 224...225, BFR 37, BFW 30, BFX 73, ++
2 N 2617	Phc	Si-N	LF, 25V, 0,1A, 0,25W	1a						BC 168, BC 183, BC 238, BC 548, ++
2 N 2618	Syl	Si-N	Uni, 60V, 0,75A, 0,6W, >200MHz	2a	TO-5					BC 140...141, BC 300...302, 2N2211...19, ++
2 N 2618/46		Si-N	=2N2618: 0,4W	2a	TO-46					BC 337A, BC 637, BC 639, 2SD667, ++
2 N 2620	Tdy	N-FET	Uni, 50V, Idss<50mA, Up<20V	2b	TO-5					-
2 N 2621	Cen,Sty	Ge-P	LF,HF, 15V, 0,1A, 0,15W, >13MHz, hFE>15	2a	TO-5					ASY 26...27, 2N1309
2 N 2622	Cen,Sty	Ge-P	=2N2621: 24V, >15MHz, hFE>15	2a	TO-5					ASY 26...27, 2N1309
2 N 2623	Cen,Sty	Ge-P	=2N2621: 32V, >16MHz, hFE>20	2a	TO-5					ASY 26, 2N1309
2 N 2624	Cen,Sty	Ge-P	LF,HF, 16V, 0,1A, 0,15W, >13MHz, hFE>15	2a	TO-5					ASY 26...27, 2N1309
2 N 2625	Cen,Sty	Ge-P	=2N2624: 24V, >15MHz, hFE>15	2a	TO-5					ASY 26...27, 2N1309
2 N 2626	Cen,Sty	Ge-P	=2N2624: 32V, >16MHz, hFE>20	2a	TO-5					ASY 26, 2N1309
2 N 2627	Cen,Sty	Ge-P	LF,HF, 15V, 0,1A, 0,15W, >13MHz, hFE>15	2a	TO-5					ASY 26...27, 2N1309
2 N 2628	Cen,Sty	Ge-P	=2N2627: 24V, >15MHz, hFE>15	2a	TO-5					ASY 26...27, 2N1309
2 N 2629	Cen,Sty	Ge-P	=2N2627: 32V, >16MHz, hFE>20	2a	TO-5					ASY 26, 2N1309
2 N 2630	Ssi,Sty	Ge-P	S, 18V, 0,1A, 0,3W, >300MHz	2a	TO-18					-
2 N 2631	USA,Rca,Tix	Si-N	VHF A,Drv, 80V, 1,5A, P<3W(150MHz)	2a	TO-39					BFS 23
2 N 2632	USA	Si-N	S-L, 90/60V, 5A, 40W, >20MHz	49m	TO-59					2N5002, 2N5004, 2N5284...85
2 N 2633	USA	Si-N	=2N2632: 120/80V	49m	TO-59					2N5284...85
2 N 2634	USA	Si-N	=2N2632: 150/100V	49m	TO-59					2N5284...85
2 N 2635	USA,Mot,Tix	Ge-P	S, 30V, 0,1A, 0,15W, >150MHz	2a	TO-18					2N2955...57
2 N 2636	USA	Ge-P	S P, 100V, 25A, 100W	23a	TO-3					2N1652...53, 2N2286...87
2 N 2637	USA	Ge-P	S P, 100V, 25A, 100W	23a	TO-3					2N1652...53, 2N2286...87
2 N 2638	USA	Ge-P	S P, 100V, 25A, 100W	23a	TO-3					2N1652...53, 2N2286...87
2 N 2639	USA,EUR	Si-N	Dual In, 45/45V, 0,03A, 0,5W, >40MHz, hFE=50...300 ΔhFE=0,9...1, ΔUbe>5mV	TO-77	(CBE-EBC-)					BFY 81, 2N2913...20
2 N 2640	USA,EUR	Si-N	=2N4639: ΔhFE=0,8...1, ΔUbe<10mV	TO-77	(CBE-EBC-)					BFY 81, 2N2913...20
2 N 2641	USA,EUR	Si-N	=2N2639: ΔhFE=, ΔUbe=	TO-77	(CBE-EBC-)					BFY 81, 2N2913...20
2 N 2642	USA,EUR	Si-N	=2N2639: hFE=100...300, ΔhFE=0,9...1, ΔUbe<5mV	TO-77	(CBE-EBC-)					BFY 81, 2N2913...20
2 N 2643	USA,EUR	Si-N	=2N2639: hFE=100...300, ΔhFE=0,8...1, ΔUbe<10mV	TO-77	(CBE-EBC-)					BFY 81, 2N2913...20
2 N 2644	USA,EUR	Si-N	=2N2639: hFE=100...300, ΔhFE=, ΔUbe=	TO-77	(CBE-EBC-)					BFY 81, 2N2913...20
2 N 2645	USA,Sgs	Si-N	Uni, 75V, 0,5A, 0,5W, >50MHz	2a	TO-18					BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 2646	Gen,Mot,Phi Tho,Tix	UJT-P	35/30V, iEM=2A, 0,3W, Ip<5mA, Iv>4mA, η=0,56...0,75, Rbb=4,7...9,1kΩ	5e	TO-72					2N4871
2 N 2646 P	Ssc	UJT-P	=2N2646: Ip<12μA	5e	TO-72					-
2 N 2647		UJT-P	=2N2646: Ip<2μA, Iv>8mA, η=0,68...0,82	5e	TO-72					-
2 N 2648	Csr,Idi	Ge-P	LFS, 30V, 1A, 0,3W, >10MHz	2a	TO-5					-
2 N 2649	Nsc	Si-N	LFS, 65V, 1A, 0,7W, >100MHz	2a	TO-5					-
2 N 2650	Nsc	Si-N	=2N2649: 140V	2a	TO-5					-
2 N 2651	USA,Fch	Si-N	S, 40V, 0,5A, 0,36W, >350MHz	2a	TO-18					BSS 10, BSX 26, BSX 39, 2N3261
2 N 2652(A)	USA,Mot	Si-N	Dual, 100V, 0,5A, 0,6W, >60MHz, ΔUbe<3mV	TO-77	(CBE-EBC-)					BFX 70...72, 2N2060, 2N2223
2 N 2654	Amp,Phc	Ge-P	VHF, 25V, 10mA, 0,1W, 250MHz	5g	TO-12	AF 239 S	5g			AF 109R, AF 139, AF 239(S)
2 N 2655	Sca,Tra	Si-N	LFS, 100V, 0,5A, 15W(Tc=25°)	2a	TO-5					BUF 49, BUY 41, 2SC1860
2 N 2656	Trw	Si-N	HF, 25V, 0,2A, 0,36W, >250MHz	2a	TO-18					BC 168, BC 183, BC 238, BC 548, ++
2 N 2657	USA,Nsc,Tix	Si-N	LFS, 80V, 5A, 4W(Tc=100°), >20MHz	2a	TO-5					BFT 32...34, 2N4895...97, 2N5336...39
2 N 2658	USA,Nsc,Tix	Si-N	=2N2657: 100V	2a	TO-5					BFT 33...34, 2N4895...97, 2N5339
2 N 2659	USA,Tix	Ge-P	LFS P, 50V, 3A, 15W(Tc=25°)	2a	TO-5					2N1039
2 N 2660	USA,Tix	Ge-P	=2N2659: 70V	2a	TO-5					2N1040