2 N 3565	Si-N	Uni, 30V, 0,05A, 0,2W, >40MHz	8a	BC 546	7a		
2 N 3566	Si-N	Uni, 40V, 0,2A, 0,3W, >40MHz	8a	BC 546	7a		
2 N 3567	Si-N	Uni, 80/40V, 0,5A, 0,3W, >60MHz, B>40	8a	BC 639	7c		
2 N 3568	Si-N	=2N3567: 80/60V	8a	BC 639	7c		
2 N 3569	Si-N	=2N3567: B>100	8a	BC 639	7c		
2 N 3611	Ge-P	NF/S-L, 40V, 7A, 77W, B>35	23a	AL 102	23a		
2 N 3612	Ge-P	=2N3611: 60V	23a	AL 102	23a		
2 N 3613	Ge-P	=2N3611: B>60	23a	AL 102	23a		
2 N 3614	Ge-P	=2N3611: 60V, B>60	23a	AL 102	23a		
2 N 3615	Ge-P	NF/S-L, 80V, 7A, 77W, B>30	23a	AL 102	23a		
2 N 3616	Ge-P	=2N3615: 100V	23a	AL 102	23a		
2 N 3617	Ge-P	=2N3615: B>45	23a	AL 102	23a		
2 N 3618	Ge-P	=2N3615: 100V, B>45	23a	AL 102	23a		
	Si-P	NF/S, 25V, 0.5A, 0.3W, <90/170ns	8a	BC 161	2a	<b>A</b> _ ,	
2 N 3638(A)			8a	BC 141	2a		
2 N 3641	Si-N	NF/S, 60/30V, 0,5A, 0,35W,>250MHz,B>40	8a	BC 141	2a		
2 N 3642	Si-N	=2N3641: 60/45V		BC 141	2a		
2 N 3643	Si-N	=2N3641: B>100	8a	BF 199	7d		
2 N 3662	Si-N	VHF/ZF, 18V, 0,025A, 0,2W, 1000MHz	7c		7 d 7 d		
2 N 3663	Si-N	VHF/ZF, 30V, 0,025A, 0,2W, 1000MHz	7c	BF 199	70		
2 N 3700	Si-N	Uni, 140V, 1A, 0,5W, 200MHz, B>100	2a	-			
2 N 3701	Si-N	=2N3700: B>40	2a	-	7-		
2 N 3702	Si-P	Uni, 40V, 0,2A, 0,3W, >100MHz, B>60	7c	BC 556	7a		
2 N 3703	Si-P	=2N3702: 45V, B>30	7c	BC 556	7a		
2 N 3704	Si-N	Uni, 50V, 0,8A, 0,36W, >100MHz, B>100	7c	BC 639	7c		
2 N 3705	Si-N	=2N3704: B>50	7c	BC 639	7c		
2 N 3706	Sì-N	=2N3704: 40V, B>30	7c	BC 639	7c		
2 N 3707	Si-N	NF-V, ra, 30V, 0,03A, 0,36W, 80MHz	7c	BC 550	7a		
2 N 3708	Si-N	NF, 30V, 0,03A, 0,36W, 80MHz,B=45660	7c	BC 550	7a		
2 N 3709	Si-N	=2N3708: B=45165	7c	BC 550	7a		
2 N 3710	Si-N	=2N3708: B=90330	7c	BC 550	7a		
2 N 3711	Si-N	=2N3708: B=180600	7c	BC 550	7a		
2 N 3712(S)	Si-N	Vid, 150V, 0,2A, 1W, >40MHz	2a	BF 259	2a		
2 N 3713	Si-N	NF/S-L, 80V, 10A, 150W, >4MHz, B>25	23a	BD 317	23a		
2 N 3714	· Si-N	=2N3713: 100V	23a	BD 317	23a		
2 N 3715	Si-N	=2N3713: B>50	23a	BD 317	23a		
2 N 3716	Si-N	=2N3713: 100V, B>50	23a	BD 317	23a		
2 N 3724	Si-N	S, 50V, 0,5A, 0,8W, >300MHz, 20/55ns	2a	-			
2 N 3724 A	Si-N	=2N3724: 1,2A	2a	-			
2 N 3725	Si-N	=2N3724: 80V	2a	-			
2 N 3725 A	Si-N	=2N3725: 1,2A	2a	-			
2 N 3730	Ge-P	TV-HA, 200V, 3A, 10W(Tc=55°)	23a	-			
2 N 3731	Ge-P	TV-HA, 320V, 10A(ss), 5W(Tc=55°)	23a	-			
2 N 3732	Ge-P	TV-HA, 100V, 3A, 3W(Tc=55°)	23a	-			
2 N 3740(A)	Si-P	NF/S-L, 60V, 4A, 25W, >4MHz	22a	BD 244 C	17j		
2 N 3741(A)	Si-P	=2N3740: 80V	22a	BD 244 C	17j		
2 N 3742(S)	Si-N	Vid, 300V, 0,05A, 1W, >30MHz	2a	MPSU 10	13m	6	
2 N 3742(S)	Si-P	Vid, 300V, 0,05A, 1W, >30MHz	2a	MPSU 60	13m		
2 N 3743(3) 2 N 3771	Si-N	NF/S-L, 50V, 30A, 150W, >0,2MHz	23a	-			
2 N 3772	Si-N	NF/S-L, 100V, 20A, 150W, >0,2MHz	23a	-			
2 N 3772	Si-N	NF/S-L, 160V, 16A, 150W, >0,2MHz	23a	MJ 15015	23a		
2 N 3773 2 N 3789	Si-P	NF/S-L, 60V, 10A, 150W, >0,2MHz NF/S-L, 60V, 10A, 150W, >4MHz, B>25	23a	BD 318	23a		
2 N 3709 2 N 3790	Si-P	=2N3789: 80V	23a	BD 318	23a		
	Si-P	=2N3789: B>50	23a	BD 318	23a		
2 N 3791		=2N3789: 80V, B>50	23a	BD 318	23a		
2 N 3792	Si-P	·	23a 7e	BF 245	23a 7f		
2 N 3819	N-FET	Uni/VHF, sym, 25V, Idss>2mA, Up<8V	7e	DI 240	/ 1		
2 N 3820	P-FET	Uni, sym, 20V, Idss>0,3mA, Up<8V	10				