

2 N 365	Csr,Etc	Ge-N	LFS, 30V, 0,05A, 0,15W, 3MHz	=1a	TO-22	AC 127, ASY 28, ASY 73...75
2 N 366	Csr,Etc	Ge-N	LFS, 30V, 0,05A, 0,15W, 3,5MHz	=1a	TO-22	AC 127, ASY 28, ASY 73...75
2 N 367	Csr,Etc	Ge-P	LFS, 30V, 0,05A, 0,1W	=1a	TO-22	AC 125...126, AC 151, ASY 26
2 N 368	Csr,Etc	Ge-P	LFS, 30V, 0,05A, 0,1W	=1a	TO-22	AC 125...126, AC 151, ASY 26
2 N 369	Csr,Etc	Ge-P	LFS, 30V, 0,05A, 0,1W	=1a	TO-22	AC 125...126, AC 151, ASY 26
2 N 370	Rca	Ge-P	HF, 24V, 10mA, 0,08W, 30MHz	1g	TO-7	AF 124...127, AF 200
2 N 370/33	Syl	Ge-P	=2N370:	5g	TO-33	AF 124...127, AF 200
2 N 371	Rca	Ge-P	HF, 24V, 10mA, 0,08W, 30MHz	1g	TO-7	AF 124...127, AF 200
2 N 371/33	Syl	Ge-P	=2N371:	5g	TO-33	AF 124...127, AF 200
2 N 372	Rca	Ge-P	HF, 24V, 10mA, 0,08W, 30MHz	1g	TO-7	AF 124...127, AF 200
2 N 372/33	Syl	Ge-P	=2N372:	5g	TO-33	AF 124...127, AF 200
2 N 373	Rca	Ge-P	HF, 24V, 10mA, 0,08W, 30MHz	1g	TO-7	AF 124...127, AF 200
2 N 373/33	Syl	Ge-P	=2N373:	5g	TO-7	AF 124...127, AF 200
2 N 374	Gen	Ge-P	HF, 24V, 10mA, 0,08W, 30MHz	5g	TO-7	AF 124...127, AF 200
2 N 375	USA,Mot	Ge-P	LFS P, 80V, 3A, 106W	23a	TO-3	2N1536...48, 2N1541...43, 2N3615...18, ++
2 N 376	USA,Mot	Ge-P	LFS P, 40V, 3A, 90W	23a	TO-3	2N1529...48, 2N2138...41, 2N2143...46, ++
2 N 376 A		Ge-P	=2N376: 50V, 5A	23a	TO-3	2N1535...38, 2N1545...48, 2N3615...18, ++
2 N 377	USA,Tix	Ge-N	S, 25V, 0,2A, 0,15W	2a(B=case)	TO-5	ASY 28...29, ASY 73...75
2 N 377 A		Ge-N	=2N377: 40V	2a(B=case)	TO-5	-
2 N 378	USA,Mot	Ge-P	LFS P, 40V, 5A, 106W	23a	TO-3	2N1529...38, 2N1539...48, 2N3611...18, ++
2 N 379	USA,Mot	Ge-P	=2N378: 80V	23a	TO-3	2N1536...38, 2N1546...48, 2N3615...18, ++
2 N 380	USA,Mot	Ge-P	=2N378: 60V	23a	TO-3	2N1535...38, 2N1545...48, 2N3615...18, ++
2 N 381	USA,Mot	Ge-P	LF Drv, 50V, 0,4A, 0,225W, 3MHz	2a(B=case)	TO-5	ASY 77, 2N1189...90
2 N 382		Ge-P	=2N381: 4MHz	2a(B=case)	TO-5	ASY 77, 2N1189...90
2 N 383		Ge-P	=2N381: 5MHz	2a(B=case)	TO-5	ASY 77, 2N1189...90
2 N 384	Sty	Ge-P	AM/FM, 70MHz	4g	TO-44	AF 106, AF 124...125, AF 200
2 N 384/33	Syl	Ge-P	=2N384:	5g	TO-33	AF 106, AF 124...125, AF 200
2 N 385	USA	Ge-N	HF/S, 25V, 0,2A, 0,15W, 6MHz	2a	TO-5	ASY 28...29, ASY 73...75
2 N 385 A		Ge-N	=2N385: 40V, 8MHz	2a	TO-5	-
2 N 386	Phc	Ge-P	LFS P, 60V, 3A, 12,5W(Tc=75°)	=23	TO-27	AL 102...103, AUY 19...20, 2N2144...46, ++
2 N 387	Phc	Ge-P	LFS P, 80V, 3A, 12,5W(Tc=75°)	=23	TO-27	AL 102...103, AUY 20, 2N2141, 2N2146, ++
2 N 388	USA,Tix	Ge-N	S, 25V, 0,2A, 0,15W, 17MHz	2a(B=case)	TO-39	ASY 28...29, ASY 73...75
2 N 388 A		Ge-N	=2N388: 40V	2a(B=case)	TO-5	-
2 N 389(A,I)	USA,Tix	Si-N	LFS P, 60V, 3A, 85W		TO-53	2N1722...23, (BD 241A, BD 535, BD 935,++) <sup>4</sup>
2 N 391	Del	Ge-P	LFS P, 50V, 5A			-
2 N 392	USA	Ge-P	LF P, 60V, 5A	23a	TO-3	2N1535...38, 2N1545...48, 2N3615...18, ++
2 N 393	Csr,Spr	Ge-P	HF/S, Chopper, 6/6/6V, 0,05A, 50MHz	37d	TO-24	-
2 N 394	USA	Ge-P	HF/S, 10/10/10V, 0,2A, 0,15W	2a(B=case)	TO-5	(ASY 26...27, ASY 48, ASY 76...77)
2 N 394 A		Ge-P	=2N394: 30/15/20V	2a(B=case)	TO-5	(ASY 26, ASY 48, ASY 76...77)
2 N 395	USA,Tix	Ge-P	S, 30V, 0,2A, 0,15W, 5MHz	2a(B=case)	TO-5	ASY 26, ASY 48, ASY 76...77
2 N 396(A)	USA,Tix	Ge-P	S, 30V, 0,2A, 0,15...0,2W, 9MHz	2a(B=case)	TO-5	ASY 26, ASY 48, ASY 76...77
2 N 397	USA,Tix	Ge-P	S, 30V, 0,2A, 0,15W, 13MHz	2a(B=case)	TO-5	ASY 26, ASY 48, ASY 76...77
2 N 398	USA,Mot,Tix	Ge-P	LFS, 105V, 0,1A, 0,05W	2a	TO-5	ACY 39, 2N2042...43
2 N 398 A		Ge-P	=2N398: 0,2A, 0,15W	2a	TO-5	ACY 39, 2N2042...43
2 N 398 B		Ge-P	=2N398: 0,25W	2a	TO-5	ACY 39, 2N2042...43
2 N 399	USA	Ge-P	LF P, -/40V, 3A, 45W(Tc=45°)	23a	TO-3	AD 149, AUY 19...20, 2N2143...46, ++
2 N 400	USA	Ge-P	LF P, 50/40V, 3A, 45W(Tc=45°)	23a	TO-3	AD 149, AUY 19...20, 2N2143...46, ++
2 N 401	USA	Ge-P	LF P, -/40V, 3A, 45W(Tc=45°)	23a	TO-3	AD 149, AUY 19...20, 2N2143...46, ++
2 N 402	USA	Ge-P	LF, 25V, 0,15A, 0,18W, hFE=25	2a	TO-5	AC 125...126, AC 151, 2SB54, 2SB56
2 N 403	USA	Ge-P	=2N402: hFE=33	2a	TO-5	AC 125...126, AC 151, 2SB54, 2SB56
2 N 404	USA,Mot,Tix	Ge-P	S, 25V, 0,15A, 0,15W	2a	TO-5	ASY 26...27, ASY 48, ASY 76...77
2 N 404 A		Ge-P	=2N404: 40V	2a		-
2 N 405	USA	Ge-P	LF, 20V, 35mA, 0,15W	1a	TO-40	AC 125...126, AC 151, 2SB54, 2SB56
2 N 406	USA	Ge-P	=2N405:	2a	TO-1	AC 125...126, AC 151, 2SB54, 2SB56
2 N 407	USA	Ge-P	HF, 20V, 70mA, 0,15W, 6,8MHz	1a	TO-40	ASY 26...27
2 N 408	USA	Ge-P	=2N407:	2a	TO-1	ASY 26...27
2 N 409	USA	Ge-P	HF, 13V, 15mA, 0,08W, 6,8MHz	1a	TO-40	AF 124...127, AF 200
2 N 410	USA	Ge-P	=2N409:	2a	TO-1	AF 124...127, AF 200
2 N 411	USA	Ge-P	HF, 13V, 15mA, 0,08W, 16MHz	1a	TO-40	AF 124...127, AF 200
2 N 412	USA	Ge-P	=2N411:	2a	TO-1	AF 124...127, AF 200
2 N 413(A)	USA	Ge-P	LF, HF, 30V, 0,4A, 0,2W	2a	TO-5	ASY 76...77
2 N 414(A,B,C)	USA	Ge-P	LF, HF, 30V, 0,4A, 0,2W	2a	TO-5	ASY 76...77
2 N 415(A)	USA	Ge-P	LF, HF, 30V, 0,4A, 0,2W	2a	TO-5	ASY 76...77
2 N 416	USA	Ge-P	LF, HF, 30V, 0,4A, 0,2W	2a	TO-5	ASY 76...77
2 N 417	USA	Ge-P	LF, HF, 30V, 0,4A, 0,2W	2a	TO-5	ASY 76...77
2 N 418	USA	Ge-P	S P, 100V, 5A, 25W(Tc=45°)	23a	TO-3	AL 102...103, AUY 28, 2N1542...43, ++
2 N 419	USA	Ge-P	S P, 55V, 3A, 25W(Tc=45°)	23a	TO-3	AD 149, AUY 19...20, 2N2144...46, ++
2 N 420	USA	Ge-P	S P, 65V, 5A, 25W(Tc=45°)	23a	TO-3	AL 102...103, AUY 28, 2N1546...48, ++
2 N 420 A		Ge-P	=2N420: 90V	23a	TO-3	AL 102...103, AUY 28, 2N1547...48, ++
2 N 421	Ben	Ge-P	LFS P, 65V, 5A			-
2 N 422	USA	Ge-P	LF, 35V, 0,1A, 0,15W	2a	TO-5	AC 125...126, AC 151, 2SB54, 2SB56
2 N 422 A		Ge-P	=2N422: 0,2A, 0,185W	2a	TO-5	AC 125...126, AC 151, 2SB54, 2SB56
2 N 424(A,I)	USA,Tix	Si-N	LFS P, -/80V, 3A, 85W		TO-53	2N1722...23, (BD 241B, BD 537, BD 937,++) <sup>4</sup>
2 N 425	USA,Tix	Ge-P	LFS, 30V, 0,4A, 0,15W, hFE>20	2a	TO-5	ASY 76...77
2 N 426	USA,Tix	Ge-P	=2N425: hFE>30	2a	TO-5	ASY 76...77
2 N 427	USA,Tix	Ge-P	=2N425: hFE>40	2a	TO-5	ASY 76...77
2 N 428	USA,Tix	Ge-P	=2N425: hFE>60	2a	TO-5	ASY 76...77
2 N 428 A		Ge-P	=2N425: hFE>80	2a	TO-5	ASY 76...77
2 N 429	Gen	Si-N				-
2 N 430	Gen	Si-N				-
2 N 431	Gen	Si-N				-
2 N 432	Gen	Si-N	30V, 0,1A, 0,15W, >10MHz	2a	TO-5	-
2 N 433	Gen	Si-N	30V, 0,1A, 0,15W, >10MHz	2a	TO-5	-
2 N 434	Gen	Si-N				-
2 N 438(A)	USA,Tix	Ge-N	LFS, 30V, 0,4A, 0,1...0,15W, >2,5MHz	2a(B=case)	TO-5	ASY 73...75
2 N 439(A)	USA,Tix	Ge-N	LFS, 30V, 0,4A, 0,1...0,15W, >5MHz	2a(B=case)	TO-5	ASY 73...75
2 N 440(A)	USA,Tix	Ge-N	LFS, 30V, 0,4A, 0,1...0,15W, >10MHz	2a(B=case)	TO-5	ASY 73...75
2 N 441	USA,Mot	Ge-P	LFS P, 40V, 15A, 150W	38a	TO-36	2N1980...82, 2N2077...78, 2N2491, ++
2 N 442	USA,Mot	Ge-P	=2N441: 50V	38a	TO-36	2N1980...82, 2N2077, 2N2081, 2N2491, ++
2 N 443	USA,Mot	Ge-P	=2N441: 60V	38a	TO-36	2N1981...82, 2N2075...76, 2N2491, ++
2 N 444	USA	Ge-N	LFS, 15V, 0,025mA, 0,1W, >0,5MHz	2a(B=case)	TO-5	ASY 28...29, ASY 73...75
2 N 444 A		Ge-N	=2N444: 40V, 0,15W	2a(B=case)	TO-5	-
2 N 445	USA	Ge-N	LFS, 15V, 0,05A, 0,1W, >2MHz	2a(B=case)	TO-5	ASY 28...29, ASY 73...75